

Quick start - PortoTube

With the Pluggerz Protect & Communicate PortoTube you can communicate via walkie talkie, while protecting your hearing.

Application

Headset for walkie talkie with air conduction tube.

The filter

The PortoTube headset has a flat filter with an attenuation of 17 dB.

The complete attenuation values are as follows:

PORTOTUBE AMBIENT+M15

FREQ.	125 HZ	250 HZ	500 HZ	1000 HZ	2000 HZ	4000 HZ	8000 HZ	SNR	H	M	L
A	19.4	18.1	17.0	16.8	17.5	17.8	18.2				
S	4.2	4.8	4.2	4.0	3.7	2.1	4.6	15	14	13	13
APV	15.2	13.3	12.8	12.8	13.8	15.7	13.6				

PORTOTUBE AMBIENT+ M20 / M25

FREQ.	125 HZ	250 HZ	500 HZ	1000 HZ	2000 HZ	4000 HZ	8000 HZ	SNR	H	M	L
A	19.4	18.1	17.0	16.8	17.5	17.8	18.2				
S	4.2	4.8	4.2	4.0	3.7	2.1	4.6	15	14	13	13
APV	15.2	13.3	12.8	12.8	13.8	15.7	13.6				


Attenuation Pluggerz hearing Protector:

A Average attenuation in dB
S Standard deviation in dB
APV Assumed protection value in dB

SNR Single number rating
H Protection value in high frequencies in dB
M Protection value in medium frequencies in dB
L Protection value in low frequencies in dB

Using the headset

You can connect the headset to the Custom-Fit earplugs by removing the filter from the earplugs. Take the grip on the earplug and gently pull it out of the earplug. Then, press the speaker of the headset in the opening of the earplug. The earplugs fit correctly when the tip points down and the L/R mark matches the L/R mark on the headset.



Note: this communication set can only be used on one side. For the right protection, use the earplug with original filter in the other ear.

This manual only applies to the communication product. For the use and maintenance of the earplugs, please consult the Pluggerz Custom-Fit manual.